


## Photoelectric lighting controller

# NightMatic 3000 Vario

EAN 4007841550516



## Functional description

Did I turn the light OFF? Or did I forget to? With the NightMatic 3000 Vario, this question's not an issue any more. When it's dark it takes care of switching the outside light ON and OFF all by itself. But that's not all: The intelligent night-economy mode automatically switches the light OFF after a programmable time and back ON again in the early hours between 4 and 5 o'clock. The photo-cell controller feels most at home on your property, on the front of a building or in a shop window.

## Technical specifications

Dimensions (L x W x H)	99 x 74 x 37 mm
Mains power supply	230 – 240 V , 50 / 50 Hz
Power consumption	0,8 W
Sensor Technology	Light sensor
Application, place	outdoors
Type of installation	Surface wiring
Twilight setting	1 – 10 lx
Switching output 1, resistive	1000 W
Switching output 1, number of LEDs / fluorescent lamps	4 stk.
IP rating	IP54
Material	Plastic
Ambient temperature	-20 – 50 °C
Colour	black
Colour, RAL	9005
Manufacturer's Warranty	3 years
Version	black