

$K\Lambda RIZM\Lambda$ [luce]






6W | AC220-240V | 50/60Hz | IP20 | Die cast | Adjustable













Do not operate with power supply connected.




To mount the track adaptor into the track system, first check that the selector knob (A) is at OFF position and the adaptor lock (B) is disengaged.






When installing the adaptor into the track, ensure that it is orientated correctly.




Rotate adaptor lock (A) clockwise 90° to connect the adaptor to the neutral circuit.






Rotate selector knob (A) to the position of desired circuit.






Circuit 1: Rotate the knob A 90° clockwise from the starting position OFF, to connect circuit 1.





Circuit 2: Rotate the knob A 90° anti-clockwise from the starting position OFF, to connect circuit 2.



Circuit 3: Rotate the knob $extbf{A} extbf{180}^{\circ}$ clockwise from the starting position OFF, to connect circuit $\ensuremath{\mathsf{3}}$



The installation is complete,

support can be freely rotated 0°-350° the lamp body can be freely rotated 90°.

Warnings:

- 1. Make sure that the product is installed properly before connecting to electricity.
- 2. Do not cover the fitting.
- 3. Maintenance and installation should only be carried out by a professional electrician.

karizmaluce.com